

# 11.6" RECESSED INTERCOM CUTSHEET v2 (see pages 2 and 3 for measurements)



## **TOUCHSCREEN**

• Brightness: 1000 Nits • Diagonal length: 11.6" • Resolution: 1920 x 1080

• Contrast ratio: 700:1

- Capacitive touch
- IP65 dust and water resistance
- Chemical resistant/ Anti-glare coated



### **COMPLETE SYSTEM**

- Bluetooth connectivity
- Touch screen withstands a 225g drop ball test from 1.6 meters
- Designed for standard power socket: NEMA 5-15
- Max temperature: +60° C/+140° F



## **DIMENSIONS**

- 14.26" x 13.9" x 2.48"
- 362mm x 354mm x 63mm



## **POWER REQUIREMENTS**

- Panel input voltage: 24VDC
- Standard power consumption: 31W at 24VDC input
- Maximum power consumption: 65W at 24VDC input
- Relay max switching current: 5A, relay max switching power: 1250W
- No AC power directly connected to panel
- Coordinate dedicated electrical circuit on UPS (power conditioned)



#### **NETWORK REQUIREMENTS**

- 2 Mbps ethernet connection Cat5e/Cat6
- No WiFi
- No DSL
- IP assigned by DHCP by default for static IP assignment call support
- 4G SIM card is supported (refer to building network requirements for details)



### **MISC.HARDWARE SPECIFICATIONS**

- Audio jack on bottom of panel for vision impaired (ADA compliant)
- For camera angle adjustment, call support

**Support:** 

P: **(571) 480-6579 ext. 2** (Mon-Fri, 6am-10pm EST)

E: support@butterflymx.com



TITLE: 11.6" Recessed Intercom Cutsheet v2


**SCALE:** Not to scale

#### SUPPORT:


P: (571) 480-6579 ext. 2 (Mon-Fri, 6am-10pm EST) E: support@butterflymx.com DRAFT SUBJECT TO CHANGE

VERSION: 11.6-F2-Cutsheet-Comp-v4-2019-9-20


**PAGE:** 2 of 3













2 INTERCOM SIDE NOT TO SCALE








3 INTERCOM PANEL BACK ELEVATION NOT TO SCALE



INTERCOM PANEL BOTTOM VIEW
NOT TO SCALE



I/O PORT

8 I/O PORT DETAIL NOT TO SCALE



TITLE: 11.6" Recessed Intercom Cutsheet v2


**DRAWING SCALE:** Not to scale

#### SUPPORT:


P: (571) 480-6579 ext. 2 (Mon-Fri, 6am-10pm EST) E: support@butterflymx.com **DRAFT SUBJECT TO CHANGE** 

**VERSION:** 11.6-F2-Cutsheet-Comp-v4-2019-9-20


**PAGE:** 3 of 3











3 SIDE VIEW: BACKBOX IN WALL NOT TO SCALE

#### **NOTES:**

- 1. COORDINATE INTERCOM PANEL ON WALL LOCATION SO TOP OF SCREEN IS 48" AFF MAX.
- 2. COORDINATE BOTTOM OF PANEL FROM FINISHED FLOOR WITH RESPECT TO MEASUREMENTS IN DETAIL #1.
- 3. COORDINATE PATHWAY OF CABLING TO 1/0 PORT LOCATION AS NOTED IN DETAIL #2 (AS VIEWED FROM FRONT ELEVATION).